

## REPACK 610 & 616



**REPACK 610**



**REPACK 616**

The REPACK is a useful tool for switching on and off non-dimmable devices such as flame effects, mirror balls, lighting fixtures with discharge lamps, black-light effects, moon flower effects etc. The Relay Pack is DMX-512 controlled and on the front panel there are six MCBs, mains switch, LED monitors and

manual ON/OFF with six push buttons. It is supplied with one CEE 5X32A plug and socket for power supply. The unit features zero crossing switch-on and programmable switch-over level. The 3-digit numeric display shows the start address which can be selected from the corresponding buttons.



**TRUSS MOUNTING**

**WALL MOUNTING**



**ACCESSORIES FOR TRUSS / WALL MOUNTING**



### REAR SIDES



**HARTING**



**CEE 17**



**SCHUKO - FRENCH  
SWISS - DANISH**

Also available with WIELAND and SOCAPEX outlets.

TECHNICAL SPECIFICATIONS	REPACK MODELS	
	610	616
NUMBER OF CHANNELS	6	6
CHANNEL CAPACITY (WATTS at 230V)	2300W	3680W
MAXIMUM CURRENT PER CHANNEL	10A	16A
SUPPLY VOLTAGE 220/240V AC 3 PHASES + NEUTRAL + EARTH ~ 50Hz	YES	YES
HOLD OF LAST DMX VALUE	YES	YES
RACK MOUNTING	YES	YES
TRUSS OR WALL MOUNTING	OPTIONAL	
DIMENSIONS IN MM (W x D x H)	483 x 25 x 88	